

# RC-SK5

# GIVE YOUR PRODUCTION A POWERFUL CREATIVE EDGE

The SKAARHOJ RC-SK5 controller, produced by world-renowned panel experts SKAARHOJ exclusively for Canon, combines Canon's XC Protocol with a professional quality joystick, zoom rocker, dials, and presets to give your multi-camera production the versatility you need to deliver videos that sparkle with fresh, creative innovation – with you at the heart.



- Create a seamless, multi-camera workflow
- Control and fine-tune with incisive control
- Monitor everything with smooth, precise control
- Enjoy versatile control with multiple control sets
- Connect to a wider SKAARHOJ ecosystem
- Link to other third-party devices  
(Additional Paid License is required)

## PRODUCT RANGE



RC-IP1000

RC-IP1000  
**RC-SK5**  
RC-IP100



**RC-SK5**



RC-IP100

The Canon logo, featuring the word "Canon" in its signature red font.

# TECHNICAL SPECIFICATIONS

# RC-SK5

<b>GENERAL</b>	
Power supply (adapter)	DC12V
Power supply (PoE)	Yes (PoE)
Exterior dimensions	W 349 x H 143 x D 179 mm
Weight	1.95 Kg
Operating temperature	0°C - 40°C
LCD Display	-
Supported protocols	XC protocol (IP) *Additional License option to open connectivity
<b>CONNECTIONS SPECS</b>	
No. of connectible cameras	10 (IP) (Registered camera is changeable from UI)
No. of camera groups	-
<b>INPUT/OUTPUT</b>	
Power supply	DC12V/PoE+
Video input/output	-
Serial Interface	-
Tally/GPIO	IP (Requires Additional License)
Video display on touch panel	-
Touch focus from screen	-
USB	YES
<b>MEMORY</b>	
Presets	Up to 100 for each camera (depends on camera specs)
Hard button support for presets	Yes
Trace	Yes
<b>CONTROL PANEL</b>	
Menu operation	Yes (20 menu sets)
No. of user buttons	-
Touch focus from panel	-
No. of camera Selectable Buttons	5+1
<b>OTHER</b>	
Initial camera settings without PC	-
Simultaneous multi-camera setup	-

## What's in the box?

- SKAARHOJ RC-SK5 Controller
- AC Power adapter/cable
- Startup Guide



Canon Inc.  
canon.com  
Canon Europe  
canon-europe.com  
English edition  
Canon Europa NV 2024